Electric Car Propulsion System

MecE 460 Capstone Design Project Winter 2008

Jason Boddez Michael Dawson Roberto Martinez Darren Achtymichuk

Objective

Differential

A Dana 44 differential

from a 1982 Corvette pro-

vides a 3.08:1 gear reduction.

A splined coupler connects the

motor directly to the differential.


Design an electric propulsion system to convert an existing Lamborghini Diablo replica car from internal combustion to electric while achieving performance comparable to a 2001 Lamborghini Diablo 6.0 VT.

Acceleration

A dynamic analysis incorporating aerodynamic drag, rolling resistance, and tractive force was used to determine the 0-100km/hr acceleration time. A 6% error in the model was estimated using published emperical data.

Range

An emperical driving profile was created to increase the accuracy of range calculations by using a data logger.



Measured Driving Profile - AMS Ventures Ltd to Nisku


Motors Modified dual Impulse

9" DC brushed motors provide 900 Nm of torque @ 0 rpm.

Changen Brusa NLG511-SA portable charger provides a charge time of 10 hours on a 240V 30A line.


Weight Distribution

Total propulsion system weight of 450kg. Resulting weight distribution:



Cost Distribution

Total cost of propulsion system: \$100,000



LamboEV Comparison

LamboEV replica car vs. 2001 Lamborghini Diablo 6.0VT

	LamboEV	Diabolo 6.0 VT
Motor	dual 9" electric	V-12 ICE
Transmission	direct drive	5-speed manual
Curb weight	3200lb	3750 lb
Weight Distribution, F/R	49/51%	41/59%
0-100km/hr time	4.8s	4.3s
Top Speed	200km/hr	330km/hr
EPA City Range	320km	420km
EPA Highway Range	280km	550km
Fill Up Cost (CAD 31/3/08)	\$4	\$120





A Café Electric Zilla motor controller provides speed control and allows for switching current direction for forward and reverse drive.

Controller

From Edmonton . . .



60 Ah Lithium Technology cells provide up to 1500A at 180V. Batteries are placed in the front and rear of the vehicle and are monitored by a battery management system.

Batteries

